



# Release Notes

## Honeywell Development Kit 1.13.2

November 14 2023

### Verifying Download Files

The release files for Honeywell Development Kit (DevKit) 1.13.2 are zip files signed with a certificate. This allows a user to verify the files they download have not been modified. After downloading the files, use the process below to verify authenticity before unzipping the files.

1. Java JDK (version 1.8 or newer) must be installed.
2. Execute the jarsigner executable against the file to verify. Example:  
`jarsigner -verify Honeywell-DevKit-1.13.2-signed.zip`

### Code Changes

Changes to code, including breaking API changes, can be found in the CHANGELOG.md file in the devkit directory, included in the DevKit zip file.

## New Features in Honeywell DevKit

### Barcode Termination Character Configuration

This feature allows specifying barcode termination characters (also called suffixes). To accomplish this, a new ScannerConfig repository has been added. This repository contains a setting called BarcodeTermination. Common entries for BarcodeTermination include:

- `\n` - newline character
- `\r` - carriage return character
- `\t` - tab character

The default is an empty string (no termination characters specified). Refer to documentation from the scanner manufacturer for more information on available termination/suffix characters.

Multiple characters may be specified. The following example entry in the OnetimeStartupSettings.config file sets CR LF (carriage return - linefeed) as the termination characters.

```
{
  "Repositories": {
    "ScannerConfig": {
      "BarcodeTermination": "\r\n"
    }
  }
}
```

## Visual Studio Support

DevKit is tested using Microsoft Visual Studio 2022 17.7.5 and Visual Studio for Mac 2022 17.6.5. These versions are recommended for future development.

# Issues Fixed in this Release

Issue Description	Issue ID
<p><b>Display Keys for Vocab Words</b></p> <p>Display keys for vocab words are not being used in the overflow menu.</p> <div data-bbox="113 520 1222 632"><p><b>NOTE</b> This fix was first included in DevKit 1.13.</p></div>	VOSMB-8324
<p><b>Barcode Termination Characters</b></p> <p>Guided Work does not handle barcode termination characters properly. A new configuration item to handle these characters is described above.</p> <div data-bbox="113 814 1222 926"><p><b>NOTE</b> This fix was first included in DevKit 1.13.</p></div>	VOSMB-7864
<p><b>Unable to Recognize "Point"</b></p> <p>The word "point" is not being recognized when attempting to input a decimal number (ex: "2 point 5) in US English using Pick Up &amp; Go.</p> <div data-bbox="113 1108 1222 1220"><p><b>NOTE</b> This fix was first included in DevKit 1.13.1.</p></div>	VOSMB-8602
<p><b>A700x Battery Drain</b></p> <p>Excessive background polling was draining the A700x battery.</p>	VOSMB-8722

## System Requirements

The following devices and software were tested for this release of DevKit.

### Minimum Android Device Specifications

- **Processor:** Qualcomm Snapdragon 410 MSM8916 1.2 GHz quad-core
- **Memory:** 2GB RAM
- **Storage:** 8GB/16GB Flash
- **WLAN:** IEEE 802.11 a/b/g/n radio
- **Bluetooth:** Bluetooth Class 4.0, Bluetooth HFP (Hands-Free Profile) version 1.6
- **Operating System:** Android N (7.0)

The above are the minimum recommended device specifications. If the device does not meet or exceed these specifications, the following symptoms may occur:

- Poor audio quality
- Slow application screen responsiveness
- Delayed input entry

# Hardware

The following devices were tested for this release.

## Honeywell Devices

- Honeywell CT30 XP
- Honeywell CT40
- Honeywell CT40 XP
- Honeywell CT45
- Honeywell CT60
- Honeywell CT60 XP
- Honeywell CN80
- Honeywell CN80G
- Honeywell CK65
- Honeywell CW45
- Honeywell ScanPal EDA51
- Honeywell ScanPal EDA71
- Honeywell A700x

## Third-Party Devices

- Zebra WT6000
- Zebra TC5x
- Zebra TC7x

## Headsets

- Honeywell SRX-SL Light Industrial Use Headset
- Honeywell SRX2 Wireless Headset (with Hands-Free Profile support)
- Honeywell SRX3 Wireless Headset

## Scanners

- Honeywell CT30 XP On-board Scanner
- Honeywell CT40 On-board Scanner
- Honeywell CT40 XP On-board Scanner
- Honeywell CT45 On-board Scanner
- Honeywell CT60 On-board Scanner
- Honeywell CT60 XP On-board Scanner
- Honeywell CN80 On-board Scanner
- Honeywell CN80G On-board Scanner
- Honeywell CK65 On-board Scanner
- Honeywell CW45 On-board Scanner
- Honeywell EDA51 On-board Scanner
- Honeywell EDA71 On-board Scanner
- Honeywell A730x On-board Scanner
- Honeywell 8670 Ring Scanner

## Android Device Operating System Support

- Android N (7.1.1)
  - Honeywell CT40
  - Honeywell CT60
- Android O (8.1.0)
  - Honeywell CT40
  - Honeywell CT60
  - Honeywell CK65
  - Honeywell ScanPal EDA51
  - Honeywell ScanPal EDA71
- Android P (9)
  - Honeywell CT40
  - Honeywell CT40 XP
  - Honeywell CT60
  - Honeywell CT60 XP
  - Honeywell CK65
- Android 10
  - Honeywell CT40
  - Honeywell CT40XP
  - Honeywell CT60
  - Honeywell CT60XP
  - Honeywell CK65
- Android 11
  - Honeywell CT30 XP
  - Honeywell CT40
  - Honeywell CT40XP
  - Honeywell CT45
  - Honeywell CT60
  - Honeywell CT60XP
  - Honeywell CK65
- Android 12
  - Honeywell CW45

## Honeywell A700x Software Support

- VoiceCatalyst 4.4 or greater

### NOTE

Honeywell A700 series and A500 devices are not supported.

## Management Server Support

- VoiceConsole 5.5 or greater

# Previously Reported Limitations

Issue Description	Issue ID
<b>Scanning Data Can Override Priority Prompts</b> Priority prompts can be overridden by scanning data at a screen where scanning is a valid input.	VOSMB-1415
<b>Voice Dialogue Continues to Run During Background Activity</b> When waiting for background spinner activity to complete, speech recognition may allow the operator to use some menu items through voice, e.g., Say Again and Help.	VOSMB-1406
<b>Do Not Press + and - Buttons on SRX3 Headset to Unpair</b> When unpairing your SRX3 headset from an Android device, do not press the + and - buttons simultaneously. This procedure causes known issues with TTS and speech recognition. <b>Proper Procedure:</b> To unpair your SRX3 headset from an Android device, go to your device Bluetooth settings, display the Paired devices screen, select the headset, and tap FORGET to unpair the headset and the Android device.	VOSMB-1448
<b>Pressing Power Button on SRX-SL or SRX2 Headset Causes Unpairing</b> If you press the Power button on your SRX-SL or SRX2 headset, the headset unpairs from the device. <b>Workaround:</b> Power off the headset and re-pair your device and headset.	VOSMB-1252
<b>"GatewayTimeout" error message from Microservices</b> If the mobile application has trouble reaching the Microservices host ("GatewayTimeout") while attempting to retrieve templates it may force the user to retrain all words for that workflow. <b>Workaround:</b> If you experience this behavior close and restart the app and log in again	VOSMB-971
<b>Do Not Press Next Button Quickly</b> If you have untrained words and get to the template training instructions screen, if you tap the Next button in rapid succession, it can cause the application to shut down unexpectedly.	VOSMB-230

Issue Description	Issue ID
<p><b>Audio to the Bluetooth Headset Can Fail</b></p> <p>In some situations, the audio no longer comes through a Bluetooth headset even though it is still paired to the device.</p> <p><b>Workaround:</b> Unpair and re-pair the headset.</p>	<p><b>VOSMB-28</b></p>
<p><b>Errors while Transmitting Files to VoiceConsole</b></p> <p>A number of errors may appear in the device logs when transmitting logs to VoiceConsole. In spite of these errors, all log files are eventually transmitted successfully.</p>	<p><b>VOSMB-570</b></p>
<p><b>State Machine Recommendation</b></p> <p>Do not create a state machine where the first state goes directly into a secondary state machine and sets the next trigger for return. The app becomes unresponsive when returning from the secondary state machine and the second state never runs.</p>	<p><b>VOSMB-465</b></p>